OSRAM PLT5 522FA_P **Datasheet**

DRAFT - For reference only. Subject to change without notice.





DRAFT – For reference only. Subject to change without notice.

Metal Can® TO56

PLT5 522FA_P

Green Laser Diode in TO56 Package

- Typical emission wavelength: 514 nm with narrow tolerance of ± 1 nm
- Excellent beam pointing accuracy





Applications

- Digital Diagnostic Devices

Features

- Optical output power (continuous wave): 50 mW (T_c = 25°C)
- Single mode semiconductor laser
- High modulation bandwidth
- Efficient radiation source for cw and pulsed operation
- TO56 package

	d)
	č	
	ř	
۰	Ħ	
	č	2
	\subseteq	
	Η	5
	7	ξ
	≤	4
	C	
	ŧ	
	≥	>
	-	
	a	١
	×	
	۷	2
	\subseteq	
	a	0
	ċ	
1	7	5
	٦	
	Ċ	b
	ĕ	
	L	
	t	j
	ā	١
	2	
	C	9
	Ξ	7
	7	5
	-/	ı
١	•	
١		
١	>	
	2	
	2	
	2	
	200	
	7 2100 0	ָ ע
	7 2100 00	
	י אומט סטכ	
		ָ כַּ
	VIOL POLICE	
	VIOL POLICIES	ַ כני כני
	VIOC accordants	
_	VIOC GOOGLE	
	reterence only	
	r reterence only	
	or reterence only	
	- or reterence only	
	Lor reterence only	
	TOT reterence	
	L For reterence only	
	TOT reterence	
	TOT reterence	
	H I HOT reterence	
	TOT reterence	
	H I HOT reterence	
	H I HOT reterence	
	H I HOT reterence	

Ordering Information			
Туре	Peak output power typ. P _{opt}	Ordering Code	
PLT5 522FA_P-M12	50 mW	Q65113A5300	

Maximum Ratings

 $T_{\rm C}$ = 25 °C

Parameter	Symbol		Values
Operating temperature	T _{op}	min.	-20 °C
	Gβ	max.	60 °C
Storage temperature	T _{stg}	min.	-40 °C
	Sig	max.	85 °C
Junction temperature	T_{j}	max.	150 °C
Forward current 1)	I _F	max.	200 mA
Reverse voltage 2)	V_{R}	max.	2 V
Soldering temperature	T_s	max.	260 °C
t _{max} = 10 s			

Operation outside these conditions may damage the device. Operation at maximum ratings may influence lifetime.

Characteristics

 P_{opt} = 50 mW (M12); T_{case} = 25°C


Parameter	Symbol		Values
Operating current 1)	l _{op}	typ. max.	115 mA 140 mA
Operating voltage ³⁾	V _{op}	typ.	6.0 V 6.9 V
Peak wavelength 4)	$\lambda_{\sf peak}$	min. max.	513 nm 515 nm
Spectral bandwidth (FWHM)	Δλ	typ.	1 nm
Beam divergence (FWHM) parallel to pn-junction	Θ	min. typ. max.	6 ° 8 ° 10 °
Beam divergence (FWHM) perpendicular to pn-junction	Θ ₁	min. typ. max.	19 ° 22 ° 25 °
Beam pointing accuracy 5)	$ \Delta \theta_{\parallel} $	min. max.	0 ° 1.5 °
Threshold current	I _{th}	typ. max.	30 mA 65 mA
TE polarization	P _{TE}	typ.	100:1
Modulation frequency	f	min.	100 MHz
Monitor current V _R = 5 V	I _m	typ.	90 μΑ
Thermal resistance junction case real	R_{thJC}	typ.	34 K / W

Wavelength Groups

Group Peak wavelength 4) Peak wavelength 4) min. max.

513 nm 515 nm M12

Dimensional Drawing 6)



Further Information:


Approximate Weight: 313.0 mg

ESD advice: ATTENTION - Observe Precautions For Handling - Electrostatic Sensitive

Device


DRAFT - For reference only. Subject to change without notice.

Electrical Internal Circuit



PIN	Description	
PIN 1	LD Cathode	
PIN 2	LD Anode, PD Cathode (case)	
PIN 3	PD Anode	


Tray 6) 50 pieces per tray




C63062-A4338-B1

DRAFT - For reference only. Subject to change without notice.

Barcode-Product-Label (BPL)



Schematic Transportation Box 6)





Notes

Depending on the mode of operation, these devices emit highly concentrated visible and non visible light which can be hazardous to the human eye. Products which incorporate these devices have to follow the safety precautions given in IEC 60825-1.

Subcomponents of this device contain, in addition to other substances, metal filled materials including silver. Metal filled materials can be affected by environments that contain traces of aggressive substances. Therefore, we recommend that customers minimize device exposure to aggressive substances during storage, production, and use. Devices that showed visible discoloration when tested using the described tests above did show no performance deviations within failure limits during the stated test duration. Respective failure limits are described in the IEC60810.

Important notes of operation for laser diode

a) Electrical operation

OSRAMs laser diodes are designed for maximum performance and reliability. Operating the laser diode above the maximum rating even for very short periods of time can damage the laser diode or reduce its lifetime. The laser diode must be operated with a suitable power supply with minimized electrical noise. The laser diode is very sensitive to electrostatic discharge (ESD). Proper precautions must be taken.

b) Mounting instructions

In order to maintain the lifetime of the laser diode proper heat management is essential. Due to the design of the laser diode heat is dissipated only through the base plate of the diode's body. A proper heat conducting interconnection between the diodes base plate and the heat sink must be maintained.

For further application related information please visit www.osram-os.com/appnotes



Disclaimer

AMS OSRAM assumes no liability whatsoever for any use of this document or its content by recipient including, but not limited to, for any design in activities based on this preliminary draft version. AMS OSRAM may e.g. decide at its sole discretion to stop developing and/or finalizing the underlying design at any time.

Attention please!

The information describes the type of component and shall not be considered as assured characteristics. Terms of delivery and rights to change design reserved. Due to technical requirements components may contain dangerous substances.

For information on the types in question please contact our Sales Organization.

If printed or downloaded, please find the latest version on our website.

Packing

Please use the recycling operators known to you. We can also help you – get in touch with your nearest sales office. By agreement we will take packing material back, if it is sorted. You must bear the costs of transport. For packing material that is returned to us unsorted or which we are not obliged to accept, we shall have to invoice you for any costs incurred.

Product and functional safety devices/applications or medical devices/applications

Our components are not developed, constructed or tested for the application as safety relevant component or for the application in medical devices.

Our products are not qualified at module and system level for such application.

In case buyer - or customer supplied by buyer - considers using our components in product safety devices/ applications or medical devices/applications, buyer and/or customer has to inform our local sales partner immediately and we and buyer and /or customer will analyze and coordinate the customer-specific request between us and buyer and/or customer.

Glossary

- Operating/Forward current: IF is measured with an internal reproducibility of ±7 % (acc. to GUM with a coverage factor of k = 3).
- 2) Reverse Operation: This product is intended to be operated applying a forward current within the specified range. Applying any reverse bias shall be avoided.
- 3) Operating/Forward voltage: VF is measured with an internal reproducibility of ±0.05 V (acc. to GUM with a coverage factor of k = 3).
- Wavelength: The wavelengths are measured with a tolerance of ±1 nm.
- 5) Beam pointing accuracy: The values may contain measurement deviations.
- 6) Tolerance of Measure: Unless otherwise noted in drawing, tolerances are specified with ±0.1 and dimensions are specified in mm.

Revision History

Version	Date	Change
α.0	2022-09-09	Initial Version
α.1	2022-09-15	Description Electro - Optical Characteristics (Diagrams) Tray Dimensions of Transportation Box
α.2	2022-10-06	Applications

DRAFT – For reference only. Subject to change without notice.



EU RoHS and China RoHS compliant product 此产品符合欧盟 RoHS 指令的要求; 按照中国的相关法规和标准, 不含有毒有害物质或元素。

Published by ams-OSRAM AG

Tobelbader Strasse 30, 8141 Premstaetten, Austria Phone +43 3136 500-0 ams-osram.com © All rights reserved



